



## LED Screen CR P4.8 Front Access Outdoor LED 5500 nit



**3840Hz Refresh Rate**



**Body Thickness Only 95mm**



**Easy Maintenance**



**IP65 Design**



**Sunlight Viewable**



**Nova Control System  
For Full Colour LED  
Display**

**Address:** Lancaster Business Park, Burton upon Trent, DE13 9PD

**Email:** [enquiries@projectdigitaluk.com](mailto:enquiries@projectdigitaluk.com)

**Website:** [projectdigitaluk.com](http://projectdigitaluk.com)

# Technical Specifications

## LED Screen CR P4.8 Front Access

### Outdoor LED 5500 nit

<b>LED Lamp</b>	SMD 3 in 1 LEDs
<b>Pixel Pitch</b>	4.81mm
<b>Brightness</b>	≥5500nits
<b>Pixels Per Panel</b>	208*208 Dots
<b>Pixel Density</b>	43,264 pixels/m <sup>2</sup>
<b>Module Size</b>	W500mm x H250mm
<b>Cabinet Size</b>	W1000mm x H1000mm x D95mm
<b>Cabinet Number</b>	3x2x2 = 12pcs
<b>Module Number</b>	12*8 =96pcs
<b>Power Consumption</b>	215W/650W per sqm(Average/Max)
<b>Ingress Protection</b>	IP65 (Front) / IP54(Rear)
<b>Material</b>	Profile aluminium
<b>Maintenance</b>	Front
<b>Resolution</b>	624*416*2 pixels
<b>Refresh Rate</b>	3840Hz
<b>Control System</b>	
<b>Sending Box</b>	Nova MCTRL300 (Only sending card function)
<b>Receiving Card</b>	Nova control system for full colour LED display
<b>Accessories, Spare Parts &amp; Package</b>	
<b>LED Module</b>	For spare
<b>Receiving Card + HUB Card</b>	For spare
<b>Power Supply (Meanwell)</b>	For spare
<b>Wooden Case</b>	For accessories & spare parts (8 in 1)
<b>Free Spare Parts</b>	
<b>LED Lamp</b>	For spare
<b>Driving IC</b>	For spare
<b>Module Mask</b>	For spare
<b>Module</b>	For spare
<b>Receiving Card + HUB Card</b>	For spare
<b>Power Supply</b>	For spare
<b>Signal Cables</b>	Between cabinets
<b>Power Cables</b>	Between cabinets